



432 Series Filler Pull-Out Instructions



Step 2. Install scribe rails to filler pull-outs using small finish nails or brads. See fig 2

Note: align scribe rails with front edge of filler pull-out. Align scribe rail to upper section of base cabinet lower mounting strap or lower section of wall cabinet lower mounting strap. See figs. 3a-b





Figure 1

Step 1. Measure scribe rail thickness and length per your specific cabinetry. See fig 1

Top Scribe Rail is nailed to bottom edge of top section

Figure 3a **Wall Cabinet**

Bottom Scribe Rail is nailed to edge of bottom section




Figure 3b **Base Cabinet**

Bottom Scribe Rail is nailed to edge of bottom section


Figure 2



Figure 4a

Figure 4b

Step 3 (Base Cabinets). Pre-drill 3/16 inch holes 3/8 inch down from top of cabinet and also 27-3/4" down from top of cabinet. (See fig 4a-d). Repeat with other adjacent cabinet.



Filler Cabinet Base Cabinet Scribe Rail Meets Face Frame




Figure 5a

Figure 5b


Step 4. Mount filler cabinet pull-out to adjacent cabinet 1. See Fig. 5a-b



Filler Cabinet **Base Cabinet** Scribe Rail Meets Face Frame

Step 5. Mount filler cabinet pull-out to adjacent cabinet 2. See Fig. 6


Figure 6



From inside the adjacent cabinet screw the 432 cabinet top.

Figure 4d **Wall Cabinet**

Screw 432 cabinet bottom from below adjacent cabinet.



Screw 432 cabinet top from above adjacent cabinet.

> Figure 4c **Base Cabinet**

From inside and above the adjacent cabinet floor screw the 432 cabinet bottom.





Step 6. Remove front mounting strap. See Fig 7a-b






Figure 9



"Changing the way you think about cabinet organization!"

